

Dear Purchaser,

Thank you for purchasing the Bree-Z Box Network Hub. I designed this package to make networking Garmin Fish finders easier and less expensive than the OEM offering. My original desire was just to save money with my new fish finders. After showcasing my success, I had many people contact me for a similar solution. At the time, my solution was very “hacky” and a little complicated. I spent months sourcing parts and testing to provide a packaged solution that is cost effective and in-line with the OEM offering. I believe I achieved this and I hope you think so as well. Thank you again and may God bless you and yours.

JaimeAstin

Instructions

Standard Package Contents

- Bree-Z Box Network Hub
- 5 Foot Network Cable
- 15 Foot Network Cable
- 2 Red Rubber “O” Rings for sealing network cable to fish finder.

Notes on Installation

- The Bree-Z Box is water resistant, but not water proof. Optionally, it is recommended that you seal network cable wires with silicon or “Marine Goop” after installation. Do not install in location exposed to elements.
- The network Cable is shielded, waterproof, UV and oil resistant. There is no concern if they are run alongside power wires or exposed to the elements.
- Bree-Z Box can be left powered on with minimum power draw.

Installation Instructions

1. Find a location to mount your Bree-Z Box. The location should not be in a location where it could flood or sprayed with water. Do not mount the Unit yet.

2. Run the network cables to your fish finder units.

3. Place the supplied “O” ring gasket on the screw connection and connect to fish finder. →



4. Open the Bree-Z Box by unscrewing the 4 screws on top. Connect the network cables from the fish finders to the port numbers “1” and “2”. Connect LiveScope to the port number “5”

Network Port Numbers				
1	2	3	4	5

**All 5 ports are live. This is a recommendation is only due to Garmin screw cable size.*

5. Mount the Bree-Z Box with four stainless steel screws upright with network cables facing down if possible. This will achieve the best water resistance.



6. Connect the Bree-Z Box to the power source. Wire can be cut if necessary.

- ◆ **Red wire is (+) Positive** and Black wire is (-) Negative
- ◆ Positive wire has a .5 or 1 AMP fuse attached.

7. Installation is complete! Power on Bree-Z Box and Enjoy.

Warranty

The Bree-Z Box has a one year warranty. The warranty covers the device under normal working conditions. This device is water resistant. Damage due to corrosion will be determined based on installation. If there is an issue with the device, please contact us for a complete resolution.

Support Email: CustomerService@techx.biz

Specifications

Power Wire	18AWG or 16AWG 600V Oil/Salt-Water/Gasoline/UV Resistant
Fuse	.5A to 1A recommended
Network Hub	Input 5V 600mA
Network Cable	Category 7 Shielded Direct Burial UV Resistant
Ports	5 x 10/100Mbps; Switching Capacity 1Gbps; Speed up to 200Mbps
Protocols	IEE 802.3i
Switch	Half& Full Duplex, MAC Address Learning, Auto Negotiation Ports, Auto MDI/MDIX Ports

*This product is not affiliated or warrantied by Garmin International.



In loving memory of Bree, 2019

Like the Bree-Z Box?

I hope you do. I hope that you like it enough to share this solution with others.

BREE-Z BOX
NETWORK HUB FOR
GARMIN FISHFINDERS



PACKAGE INCLUDES:
▶ WATER RESISTANT HUB*
▶ 5 NETWORK PORTS
▶ 15' & 5' NETWORK CABLE**
▶ FREE SHIPPING

SAVE OVER \$125
COMPARED TO GARMIN **\$150**

If anyone purchases a Bree-Z Box and mentions that they heard it from you, I will send you a \$10 Amazon Gift Card for each order, no limit. I will ask the purchaser how they heard about the Bree-Z Box and if they provide your "Full Name", you will receive an email with the Gift Card after they complete their order. I just want to say THANK YOU!

If you have any feedback, I would love to hear it. Let me know if you ever make a post/video on YouTube or Facebook. To make things easier, I am enclosing a few cards to hand out.

Thank you again.

